

Viviana 12 & 15 Light Pendant Fitting

INSTRUCTION MANUAL

Safety Warnings

- This product is only suitable for connection to a 240V~50Hz supply in accordance with current IEE wiring regulations. It should be installed in accordance with local building regulations and is for domestic use only. It is not suitable for a bathroom location.
- Before installing your light fitting always switch off the mains supply and remove the appropriate fuse or switch off the appropriate circuit breaker before commencing installation.
- This is a Class I fitting, and **must** be connected to Earth. The terminal blocks are supplied according to requirements of the fitting.
- Never fit bulbs of a higher wattage than those specified on the label, as this may cause overheating and damage the fitting.
- This product contains delicate parts – be careful during handling and maintenance to avoid breakage.
- This product is **very heavy (12-light: 16kg; 15-light: 23kg)**. Please ensure you have appropriate assistance, and use caution during installation and maintenance. Only use the chain provided, and ensure the fitting is attached to a surface that can take its weight.
- If you are in any doubt about your competence please consult a qualified electrician.
- If any modification is made it will invalidate the warranty and may render the product unsafe.
- Allow 10 minutes to cool before performing maintenance. Clean with a dry cloth only. Do not use liquid or abrasive cleaners on this product.

Assembly/ User Instructions

Before you start

Please read these instructions carefully before fitting and retain for reference. Check the packaging and make sure that you have all the required parts. Follow each assembly step in order to prevent incorrect assembly. Ensure that the product is fully assembled as illustrated before use.

This instruction covers both 12 and 15 light versions of the fitting.

The Light pack contains:

Light fitting.
Fixing pack.
3x crystal frames
3x connection rods marked "A" (230mm)
6x connection rods marked "B" (130mm)

The following tools may be required:

Selection of cross and flat head screwdrivers.
Electric drill and assorted drill bits.
Wire strippers.
Electrical insulation tape.

These assembly diagrams are intended as a guide – if in doubt consult a qualified electrician.

1. Decide on the position of the light fitting, or remove existing light fitting. Note the position of the electrical connections. This fitting is **very heavy**. It is vital to ensure there is a solid mounting surface, preferably a wooden joist or joist bridge, that will support the weight of the light fitting.
2. Use the fixing bracket (9) as a template to mark the screw holes, and secure to the ceiling with appropriate screw fixings (8&10).
3. If you want to reduce the overall length of the fitting it is essential that this is done before the fitting is mounted to the ceiling, or connected to the mains supply. Remove the chain links until the desired length is reached. The cable must now be shortened and the excess cable cut and re-connected to the terminal block. Feed the cable up through the plastic bush and form a loop above the ceiling cup, moving the figure of 8 cable restraint down the exposed cable. **NOTE: The electric cable must always be longer than the chain to prevent strain being placed on the cable. If you are unsure about your ability to do this, we recommend you contact a qualified electrician.**
4. This product is packed as 3 separate sections. Before installation it is necessary to re-assemble the sections. Firstly, screw the suspension tube (7) onto the thread in the centre of the middle section. Tighten the tube securely by hand.
5. Fit the 6 rods marked "B" (130mm) (4) onto the small threads on each of the struts on the middle section. Carefully screw them securely to the top frame



Assembly/ User Instructions Continued

6. Now fit the top section to the middle section. Feed the ceiling cover and cable through the centre of the top section and align the holes in the struts with the 6 rods fitted to the middle section. Remove the screws from the tops of the 6 rods and refit - securing the top section in place.
7. At this point, the product can be fitted to the ceiling prior to fitting the bottom section. This will reduce the weight of the product for installation. If you prefer to assemble the entire product before installing - please continue from step 10.
8. Support your fitting, using additional persons, and connect the house wiring to the terminal block (11) – see expanded wiring details. **NOTE: This is a Class I fitting and must be earthed.** The 4th terminal block connector is used for the “loop” wires of the “Ring Circuit”. There may be more than one set of cables in the “loop” connections. If there is a “Ring Circuit” and you do not understand the connections you must consult an electrician. Any loose terminal blocks – not secured to ceiling cup – should always be covered with 2 layers of good quality insulation tape.
9. Secure the ceiling cup over the bracket by using the finials (12), Fit the bulbs (6). **NOTE: Never fit bulbs of a higher wattage than those specified on the label (as these may cause overheating and damage the fitting).** then turn on the power and test.
10. Fit the 3 rods marked “A” (230mm) (2) to the lower struts of the middle section. Remove the screws and set aside.
11. Attach the lower section to the product by aligning the holes in the struts with the 3 rods. Refit the screws (3) and tighten to secure.
12. Ensure the product hangs level and all sections are securely fitted together.

Assembly/ User Instructions Continued

